

LT-1-DM-1310



DEVICE

DM Transmitter - 1310 nm

OVERVIEW

The Optilab LT-1-DM-1310 series laser transmitters are reliable and costeffective for HFC, FTTH and deep fiber applications. The LT-1-DM-1310 uses a highly linear 1310 nm, 1510 nm DFB laser module and an advanced predistortion RF drive circuit to deliver 50 dB of CNR, while maintaining optimal CSO and CTB distortion specifications.

The LT-1-DM-1310 has a standard transmission range up to 20 km. The LT-1-DM-1310 transmitters support up to 75 NTSC analog channels and since it is designed to be digitally ready, these transmitters can be loaded with 60 additional QAM modulated signal channels.

The LT-1-DM-1310 is available at five output power levels: +6 dBm, +8 dBm, +10 dBm, +11 dBm and +13 dBm.

FEATURES

- Highly linear, analog-modulated 1310 nm, 1510 -20 dB front panel RF test port nm DFB laser source
- Advanced pre-distortion circuit minimizes CSO and CTB distortion
- Automatic Gain Control (AGC) for optimal RF drive level
- 75 channel NTSC plus 60 digital channels loading plan

- LED front panel digital display and status indicators
- 45 MHz to 870 MHz modulation bandwidth

USE IN

- HFC
- FTTH

- RFoG
- Deep Fiber Applications





LT-1-DM-1310

TECHNICAL SPECIFICATIONS

Transmission Range Output Power Level 6 dBm, 8 dBm, 10 dBm, 11 dBm, 13 dBm Number of Outputs 1 output standard, multiple output can be ordered Optical Return Loss 50 dB min. Carrier to Noise Ration (CNR) 52 dB TYP. ■ 0 dBm Composite Second Order (CSO) Distortion Composite Triple Beat (CTB) Distortion RF Test Port Ratio 1 output standard, multiple output can be ordered 1 output standard, multiple output can be ordered 1 output standard, multiple output can be ordered 2 of dB min. 52 dB TYP. ■ 0 dBm -60 dBc max. -60 dBc max.	aser Wavelength Range	1310 nm ± 15 nm
Number of Outputs Optical Return Loss Carrier to Noise Ration (CNR) Composite Second Order (CSO) Distortion Composite Triple Beat (CTB) Distortion I output standard, multiple output can be ordered and be ordere	ransmission Range	Up to 20 km in SMF-28 fiber
Optical Return Loss Carrier to Noise Ration (CNR) Composite Second Order (CSO) Distortion Composite Triple Beat (CTB) Distortion 50 dB min. 52 dB TYP. 20 dBm -60 dBc max.	Output Power Level	6 dBm, 8 dBm, 10 dBm, 11 dBm, 13 dBm
Carrier to Noise Ration (CNR) Composite Second Order (CSO) Distortion Composite Triple Beat (CTB) Distortion 52 dB TYP. 20 dBm -60 dBc max.	lumber of Outputs	1 output standard, multiple output can be ordered
Composite Second Order (CSO) Distortion Composite Triple Beat (CTB) Distortion -62 dBc max.	Optical Return Loss	50 dB min.
Distortion Composite Triple Beat (CTB) Distortion -62 dBc max.	Carrier to Noise Ration (CNR)	52 dB TYP. 🛽 🛭 dBm
	·	-60 dBc max.
RF Test Port Ratio -20 dB	Composite Triple Beat (CTB) Distortion	-62 dBc max.
	Pract Port Ratio	-20 dB
AGC Adjustment Range (Optional) 6 dB	AGC Adjustment Range (Optional)	6 dB
Input RF Power Level 13-18 dBmV per Channel	nput RF Power Level	13-18 dBmV per Channel
Frequency Range 45 MHz to 870 MHz	requency Range	45 MHz to 870 MHz
Flatness in Frequency Range ±0.75 dB	latness in Frequency Range	±0.75 dB
Input Impedance 75Ω	nput Impedance	75 Ω
Input RF Return Loss 16 dB min.	nput RF Return Loss	16 dB min.

MECHANICAL SPECIFICATIONS

Operation Temperature Range	0°C to +50°C
Storage Temperature Range	-40°C to +70°C
Power Supply	80-240 V, 43-63 Hz AC
Power Consumption	3D W max.
Housing Dimensions	1U Rack: 19"(W) x 14"(D) x 1.75"(H)
Control / Monitoring	DFB Laser Temperature and Current
Display	Output Power Level, TEC temperature
Alarm	Over Temperature, Over Current
Optical Connectors	SC/APC or Customer Specified

